

PR1210, PR1210L, PR2410, PR2410L

Charge Controller



- Compact, potted Design
- Can be mounted in panel junction box
- For sealed/vented batteries
- High quality charging regime

The PR series is a two stage controller for charging lead acid batteries from photovoltaic panels. The full available charge current is allowed to flow into the battery until the battery voltage rises to the boost maximum. The battery now being fully charged, the unit switches to the float mode. The current is switched off and the battery voltage slowly falls. When it drops below the float cut in, the current is switched on again. It stays on until the voltage rises to the float maximum and is then turned off. The battery voltage will slowly oscillate between the float maximum and cut in. When the battery has been discharged enough for it to fall below the boost cut in, the unit will switch back into the boost mode. The PR uses a rugged power mosfet and switches on the negative side.

Solar positive connects either direct to the battery positive terminal or to the bat+ on the controller.

The unit fits into standard solar panel terminal blocks. It does not contain a reverse blocking diode.

TYPE	PR1210/PR1210L	PR2410/PR2410L
Voltage	12V	24V
Max. module current	10A	10A
Battery type	Vented/sealed (L version)	Vented/sealed (L version)
Dimensions(WxHxD)	38 x 63 x 19mm	38 x 63 x 19mm
Self power consumption	4mA	4mA

Phocos AG, Germany
info@phocos.com

Phocos China Ltd., China
Info-china@phocos.com

Phocos India Solar Pvt. Ltd., India
Info-india@phocos.com

Phocos Latin America S.R.L, Bolivia
Info-latinamerica@phocos.com

Phocos Rep. Office Australia, Australia
Info-australia@phocos.com

Phocos Rep. Office Brazil, Brazil
Info-brazil@phocos.com

Phocos Rep. Office Eastern Africa, Kenya
Info-easternafrica@phocos.com

Phocos Eastern Europe S.R.L., Romania
Info-easterneurope@phocos.com

Phocos SEA Pte Ltd, Singapore
Info-sea@phocos.com

Phocos Rep. Office South Africa
Info-sadc@phocos.com

Phocos Tunisia
Info-maghreb@phocos.com

Phocos USA
Info-usa@phocos.com